

RE3-ACC-CXU25 25 foot, 50 ohm low loss BNC coax cable

- Premium low-loss coax cable
- Robust BNC connectors
- Robust male BNC connectors



The CXU25 is a premium-grade, low-loss coax cable for UHF wireless microphone systems. Its high-efficiency and low-attenuation characteristics make it ideal for system installations requiring extended cable runs between antennas and receivers.

Technical specifications

Cable type:	Coaxial
Connector type:	BNC - BNC
Impedance:	50 ohms
Estimated attenuation at length:	1.3 dB
Dimensions (length):	25' (7.62 m)
Diameter:	0.240" (6.1 mm)
Color:	Black
Net weight:	13.4 oz. (380 g)
Gross weight:	14.05 oz. (410 g)

Installation/configuration notes

To install the coax cable, do the following:

1. Insert the cable-mounted male BNC connectors onto antenna jacks at receiver (or splitter) and antenna.
2. Turn connector clockwise to lock BNC connectors onto BNC jacks.

Compatible products

Order number	Description
RE3-ACC-RMK1	Rack mount kit for single RE3 receiver
RE3-ACC-RMK2	Rack mount kit for two RE3 receivers
RE3-ACC-CXUF	Rear to front mount antenna cable kit
RE3-ACC-PLPA	Passive log periodic antenna, 470-960MHz
RE3-ACC-ALPA	Active log periodic antenna, 470-960MHz
RE3-ACC-AASP	2-in x 8-out antenna splitter 470-960MHz
RE3-ACC-PASP	1 x 2 passive antenna splitter kit
RE3-ACC-RFAMP	Active RF antenna booster, 470-960MHz

Parts included

Quantity	Component
1	50 ohm antenna cable
1	Engineering datasheet
1	Warranty and product documentation information card

Ordering information

RE3-ACC-CXU25 25 foot, 50 ohm low loss BNC coax cable

25 foot, 50 ohm low-loss BNC coax cable for UHF wireless systems, black

Order number **RE3-ACC-CXU25**

Represented by:

Germany:

Bosch Sicherheitssysteme GmbH
Robert-Bosch-Ring 5
85630 Grasbrunn
Germany

Bosch Security Systems, Inc.
12000 Portland Avenue South
Burnsville MN 55337
USA

www.electrovoice.com