



Dx46

FIR-DRIVE SOUND SYSTEM PROCESSOR

Born of the legacy of such legendary DSPs as the Dx34, Dx38 and N8000, the Dx46 combines ease of use and flexibility of control with the industry's most advanced DSP technology: FIR-Drive.

FIR-Drive

The Dx46 brings the same technology found in NetMax and RCM-26 equipped Tour Grade amplifiers to a new, compact and easy to use form factor. Providing six channels of 512-tap, complex phase FIR filters in addition to EV's state of the art PA Limiter and TEMP Limiter algorithms

Connectivity Your Way

The Dx46 provides a USB interface for convenient local connection as well as an Ethernet interface with an integrated switch for more advanced and networked connectivity. Additionally, five GPI ports provide input for contact closures or other hardware interfaces.

IRIS-Net

IRIS-Net allows complete integration of your EV sound system, including amplifiers, external controls, amplifiers and much more. Providing complete control, configuration, and supervision through standard or customized interfaces, IRIS-Net allows the ultimate in flexibility for controlling what you want to control-how you want to control it.

Advanced DSP Options

The Dx46 provides complete input processing, with graphic EQ, PEQ and delay. You also get a complete FIR-Drive outputs stage including crossover, EQ and dynamics. But the Dx46 goes further providing specialized Array EQ and Array Delay blocks on each output. Configuring and adjusting highly specialized array, cluster or zoned systems has never been more convenient.



- ▶ 2x6 FIR-Drive loudspeaker processor
- ▶ Analog and AES/EBU inputs
- ▶ Full IRIS-Net control and configuration
- ▶ Ethernet and USB data interfaces
- ▶ Full loudspeaker protection package including PA and TEMP limiters
- ▶ Dedicated array EQ and delay sections for advanced applications
- ▶ -6dB switchable analog pad inserted before A/D converters on inputs
- ▶ 4 Separate delay sections
- ▶ 5 Contact closure inputs
- ▶ 60 Factory presets
- ▶ 30 User presets
- ▶ Unique Edit/Compare mode



Property	Value
Mains Voltage	100 to 240V, 50 to 60Hz
Power Consumption	25W
Analog Audio Inputs	2xXLR In, electronically balanced 2xXLR Through, electronically balanced
Digital Audio Inputs	1xXLR AES/EBU In 1xAES/EBU Out
Digitales Audio Format	AES3, 32 kHz to 192 kHz Sample Rate
Nominal Input Voltage	1,55 V / + 6 dBu
Maximum Input Voltage (with -6dB PAD engaged)	17,3 V / + 27 dBu
Input Impedance	10kΩ
Common Mode Rejection	-85 dB
A/D Conversion	24-Bit Delta Sigma
Analog Audio Outputs	6 x XLR Out, electronically balanced
Nominal Output Voltage	1,55 V / + 6 dBu
Maximum Output Voltage	8,7 V / + 21 dBu
Output Impedance	50Ω
D/A Conversion	24-Bit Delta Sigma
Frequency Response	20 Hz to 40 kHz (-3 dB)
THD+N	<0,002% (band limited 20 Hz to 20 kHz)
Dynamic Range	116 dB (A-weighted)
USB	USB type B on front panel (PC Interface)
Ethernet	2xRJ45
Control Port	1x6 pole Euro Block Software Configurable for Preset Recall
Sample Rate	48 kHz
Daa Format	24-Bit
Internal Processing	48-Bit Double Precision
Operating Temperature Range	0°C to +40°C
Dimensions (WxHxD)	483x356,1x43,6 mm
Weight (Net)	4.8 kg

Bosch Communications Systems

Americas
Headquarters Americas
Bosch Security Systems, Inc.
 12000 Portland Ave South,
 Burnsville, MN 55337, USA
 USA-Ph: +1 800 392 3497
 Fax: +1 800 956 6931
 Canada-Ph: +1 866 505 5551
 Fax: +1 866 336 8467
 Latin America-Ph: +1 952 887 5532
 Fax: +1 952 736 4212

EMEA
Headquarters Europe,
Middle-East & Africa
Bosch Sicherheitssysteme GmbH
 Werner-von-Siemens-Ring 10
 85630 Grasbrunn, Germany

Contact & Visitor Address
EVI Audio GmbH
 Sachsenring 60
 94315 Straubing, Germany
 Phone: +49 9421 706 0
 Fax: +49 9421 706 265

France
EVI Audio France S.A.S
 Phone: +33 1 64.80.00.90
 Fax: +33 1 60.06.51.03

Middle East
Robert Bosch
Middle East FZE
 Phone: +97 14 212 3300
 Fax: +97 14 212 3388

Asia & Pacific
Headquarters APR
Robert Bosch (SEA) Pte Ltd
 11 Bishan St. 21
 Singapore 573943
 Phone: +65 6571 2526
 Fax: +65 6571 2699

Australia
Bosch Security Systems Pty Ltd
 Phone: +61 2 9683 4752
 Fax: +61 2 9890 5928
China
Telex EVI Audio
(Shanghai) Co., Ltd.
 Phone: +86 21 6317 2155
 Fax: +86 21 6317 3025
Korea
Robert Bosch Korea
 Phone: +82 31 270 4765
 Fax: +82 31 270 4601

China
Telex EVI Audio
(Shanghai) Co., Ltd.
 Phone: +86 21 6317 2155
 Fax: +86 21 6317 3025
India
Bosch Limited
 Phone: +91 80 4176 8378
 Fax: +91 80 4176 8263
Japan
EVI Audio Japan
 Phone: +81 3 5485 4427
 Fax: +81 3 5485 4428

